

Vision Software Update


Latest version released: 1.15M

Attention, the software update can only be performed from a compatible Microsoft Windows computer.

Download the latest version of the software: 115M.rar (One of the following software is required to decompress the file: Winzip, 7-Zip, WinRAR)

Just a USB stick is needed (possibly formatted to avoid any kind of conflict) and follow the instructions below:

1. Check the software version in your oven via the control panel. (**Settings> Information> FW Display Line 1**).
2. If the version of your software is less than the updated version, download the Zip file "115M.rar" that you find at the top of this page.
3. Once the Zip file has been downloaded, unzip / unpack it, then copy all the files extracted into a USB key (maximum size 16 GB, formatted in FAT32).

 loading	24/01/2020 09:44	File PNG	21 KB
 md5	24/01/2020 10:59	File	1 KB
 md5_error	05/08/2018 21:58	File PNG	61 KB
 mnbtdr	12/09/2018 16:51	File	1 KB
 upgrade	24/01/2020 10:59	WinRAR archive	107.781 KB
 worker	02/08/2018 14:35	File	2 KB

4. Insert the key into the USB port on the VISION control unit (with the oven powered, even in the black screen).
5. Read the instructions on the VISION screen that will warn you when it is time to remove the USB stick.
6. Wait about 1 minute for the card to give the coloured power button (it means that the update was successful and you can turn on the oven). Check on the **Settings> Information> FW Display Line 1** page that the software displayed is 1.15B

Update Vision Keyboard Software

Latest version released: Keyboard 1.15

Attention, the software update can only be performed from a compatible Microsoft Windows computer.

Download the latest version of the keypad software: Keyboard1.15.rar (One of the following software is required to decompress the file: Winzip, 7-Zip, WinRAR)

Just a USB stick is needed (possibly formatted to avoid any kind of conflict) and follow the instructions below:

1. Once the Zip file has been downloaded, unzip / unpack it, then copy all the files extracted into a USB key (maximum size 16 GB, formatted in FAT32).

kpd_update	30/01/2020 14:38	Cartella di file	
loading_fw	29/01/2020 16:39	File PNG	16 KB
mnbtdr	25/07/2019 15:18	File	2 KB
README	13/06/2017 07:34	Documento di testo	1 KB
update_completed	15/07/2019 17:09	File PNG	18 KB

2. Insert the key into the USB port on the VISION control unit (with the oven powered)
3. The upgrade icon will appear, the installation will be successful when the information will be shown in the screen.

4. At this point, wait the reboot, then remove the USB key.

5. Wait about 1 minute for the card to give the coloured power button (it means that the update was successful and you can turn on the oven). Check on the **Settings> Information> FW Display Line 5** page that the software displayed is 1.15

If the procedure is not completed, switch the oven off, remove the USB stick and switch the oven back on, check **Settings> Information> FW Display Line 5** for the set version, repeat the update operation from point 2.

